


Sagemcom

F@ST PLUG 501P DUO

Powerline Communication device For high performance and efficient network

- 500 Mbps •
- Additional socket with integrated noise filter •
- Works with all internet access boxes / gateways*
 - Encrypted communications
 - Easy installation •





F@ST PLUG 501P DUO

APPLICATIONS

Streaming / Gaming / Networking

- Smart TV, HD and 3D optimized throughput and coverage
 - High speed broadband transmission •
 - Simple set up to share PC files, printers, IP cameras...
 - Ideal for online gaming •

MAINS SPECIFICATIONS

500 Mbps data transmission rate**

Additional socket with integrated noise filter

1 Ethernet Port

Quality of service management

128-bit AES Link Encryption with key management

Power management

**Maximum throughput based on theoretical transmission PHY rate

STANDARDS

HomePlug AV

IEEE 1901

Eup regulation 1275 / 2008 : less than 1 watt in standby mode

Auto MDI / MDI-X: detection of Ethernet cables crossed

COEXISTENCE & COMPATIBILITY

Co-existence with HomePlug® 1.0 devices (14Mbps) and HomePlug® 1.0 Turbo devices (85Mbps)

Works with HomePlug AV® devices: 200 Mbps

BOX CONTENT

2 x F@ST PLUG 501P

2 x White Ethernet cables with RJ45 connectors

1 x Quick Start Guide

HARDWARE

Chipset AR7420

1 x Female Power Socket Type E or Type F or Type G

1 x Male Power Plug type E, E+F or type G

1 x Button Press Encryption with key management

1 x Power activity LED

1 x Powerline activity multicolor LED

1 x Ethernet Link Activity LED

1 x Ethernet Port (Auto MDI / MDI-X)

Dimensions (mm): 113 x 60 x 85

Weight: 194g

POWER AND CONSUMPTION

Power: 100-240V AC 50-60Hz

Maximum consumption: 2,5W

Idle consumption: 0,5W

TEMPERATURE & ENVIRONMENT

Operating Temperature: 0°C to 45°C

Max Relative Humidity (non condensing): 90%

The information and specifications included are subject to change without prior notice. Sagemcom Broadband tries to ensure that all information in this document is correct, but does not accept liability for error or omission. Non contractual document. All trademarks are registered by their respective owners. Simplified joint stock company - Capital 35.703.000 Euros - 518 250 360 RCS Nanterre. 06/2013

Sagemcom Broadband SAS

Headquarters: 250, route de l'Empereur 92848 Rueil-Malmaison Cedex - FRANCE

Tel: +33 (0)1 57 61 10 00 - Fax: +33 (0)1 57 61 10 01

SageMcoM