Sagemcom

F@ST PLUG 502W

Powerline Communication device To extend your Wi-Fi <u>network</u>

- PLC data transmission rate : 500Mbps
 - Wi-Fi: 300Mbps •
 - 2 Ethernet Ports •
- Works with all internet access boxes / gateways*
 - Easy set-up •



F@ST PLUG 502W

APPLICATIONS

- Broadband Internet network extension over Wi-Fi •
- Connection of Smartphone or tablet anywhere in the house ullet
 - Streaming / Gaming over Wi-Fi or Ethernet
 - IPTV, IP Camera over Wi-Fi or Ethernet •
 - Sharing files and devices over Wi-Fi or Ethernet •

MAINS SPECIFICATIONS

したたらう

0

PLC data transmission rate: 500Mbps**

Wi-Fi data transmission rate: 300Mbps**

2 Ethernet Ports

Quality of service management

128-bit AES Link Encryption with key management

Power management

** Maximum throughput based on theoretical transmission PHY rate

STANDARDS

IEEE 1901

IEEE 802.11 b,g,n

COEXISTENCE & COMPATIBILITY

Coexistence with HomePlug® 1.0 devices (14Mbps) and HomePlug® 1.0 Turbo devices(85Mbps)

Works with HomePlug AV® devices: 200 Mbps

BOX CONTENT

1 x F@ST PLUG 502W

1 x White Ethernet cable with RJ45 connectors

1 x Quick Start Guide

POWER AND CONSUMPTION

Power : 100 - 240V AC 50 - 60Hz

Maximum consumption : 5,5W

Idle consumption : 0,2W

HARDWARE

Chipset AR7420 + Chipset AR9341
1 x Male Power Plug type E, E+F or type G
1 x Button ON/OFF switch
1 x Button Press Encryption with key management
$1 ext{x}$ Button pairing Wi-Fi (short press) - Wi-Fi ON/OFF (long press)
1 x Button reset
1 x Power activity LED
1 x Powerline activity multicolor LED
1 x Wi-Fi activity LED
2 x Ethernet activity multicolor LED
2 x Ethernet Ports (Auto MDI/MDI-X)
1 x Configuration interface html onboard
Dimensions (mm) : 107 x 62 x 49

Weight : 183g

TEMPERATURE & ENVIRONMENT

Operating Temperature: 0°C to 45°C Max Relative Humidity (non condensing) : 90%

All rights reserved. The information and specifications included are subject to change without prior notice. Sagemcom Broadband tries to ensure that all information in this document is correct, but does not accept liability for error or omission. Non contractual document. All trademarks are registered by their respective owners. Simplified joint stock company - Capital 35.703.000 Euros - 518 250 360 RCS Nanterre. 07/2013

Sagemcom Broadband SAS Headquarters : 250, route de l'Empereur 92848 Rueil-Malmaison Cedex - FRANCE Tel : +33 (0)1 57 61 10 00 - Fax : +33 (0)1 57 61 10 01 www.sagemcom.com

